

NXP JCOP Javacard

NXP JCOP [] NXP [] Javacard [] NXP [] Javacard []

[]

J3 A 080 G dd(d) / T 0B rr ff o

- J = NXP JCOP
 - J5=NFC(S2C)
 - J3=Dual IF,CD=PKI+DES
 - J2=CT,CD=PKI+DES
 - J1=CT,DES
- A = JCOP version
 - A=JCOP 2.4.1 R3(Java Card 2.2.2 GP 2.1.1)
 - C=JCOP 2.4.2 R1
 - D=JCOP 2.4.2 R2(Java Card 3.0.1 GP 2.2.1)
 - E=JCOP 2.4.2 R3(Java Card 3.0.1 GP 2.2.1)
 - G=JCOP 3.0
 - H=JCOP3 P60-2
 - O=JCOP 4.0
 - Q=JCOP 4.2
- 080 = EEPROM Size 80K
- G = JCOP type
 - G=Java Std-Generic
 - V=Java Std-VISA
 - C=Java Std-Customized
 - M=Java Std-MasterCard
 - C=Java Static-Generic
 - U=Java Static-VISA
 - T=Java Static-MasterCard
- dd(d) = Delivery type
 - UA=sawn wafer 150u FFC
 - X0=PDM module
 - A4=MOB4
 - A6=MOB6
 - HN1=HVQFN32 package
- T = FAB ID
- 0B = HW Version
- rr = ROM code ID

- ff = FAB key ID
- o = Option
 - 0=no Mifare
 - 1=1k Mifare
 - 4=4k Mifare
 - 7=7k DESFire
 - 8=8k DESFire

XXXXXXXX

IDENTIFY XXX 00A4040009A000000167413000FF00

XXXXXXXX

Offset	Size	Name	Base mask value
0	1	FABKEY ID	xxh (customer dependent)
1	1	PATCH ID	xxh (see Patch ID in Administrator Manual)
2	1	TARGET ID	00h
3	1	MASK ID	33h (mask51)
4	4	CUSTOM MASK ID	00h 00h 00h 00h [1]
8	6	MASK NAME	NX011C
14	1	FUSE STATE	00h (not fused) or 01h (fused)
15	1	ROM INFO LENGTH	03h
16	3	ROM INFO [2]	J3A080 and J2A080: EDh 10h 3Ch J3A040 and J2A040: 23h B7h 16h

Revision #3

Created 2019-08-14 11:39:34 CST by ZZ

Updated 2019-08-14 11:50:29 CST by ZZ